

## FEATURES AND SPECIFICATIONS

- 6 double-pole double-throw relays rated at 5 Amps. 30 volts DC.
- 2 normally open and 2 normally closed contacts per relay.
- Six 6-terminal screw-type plug-in connectors - one for each of the relays.
- Each relay and the relay poles are isolated from each other allowing use in circuits of differing potentials and grounds.
- 4-terminal IR IN and +12V plug-in for Xantech IR Receivers, Smart Pads, connecting blocks and other devices.
- IR Confirm LED lights with RC68+ and non RC68+ IR signals.
- RC68+ IR commands permit **Pair**, **Toggle**, **Momentary** and **Group** mode operations as well as different IR codes for use of multiple CC62's.
- The CC62's Code Group number is **60**.
- Universal mounting fits 19-inch racks or any 3-1/2" X 19" flat surface. Extends about 2-3/4" behind panel with cables connected.
- Requires RC68+ (or RC68) Programmer and 782-00 Power Supply.
- Power: 12 VDC @ 300mA.
- Dimensions: 19" W x 3-1/2" H x 2-1/4" D